

# Linksys Router Port Forwarding Setup for Viewtron DVR

1. Log into your Linksys Router by typing the following gateway into a web browser <http://192.168.1.1> [By default Username and Password are both **admin**]
2. Once you are logged into your Linksys router click "**Applications & Gaming**" > "**Single Port Forwarding**". [If "Single Port Forwarding" is not an option than select "Port Range Forwarding"]

The screenshot displays the Linksys router's web interface for configuring port forwarding. The top navigation bar includes 'Applications & Gaming', 'Setup', 'Wireless', 'Security', 'Storage', 'Access Restrictions', 'Applications & Gaming', 'Administration', and 'Status'. The 'Applications & Gaming' section is active, and 'Single Port Forwarding' is selected. The main content area features a table for configuring port forwarding rules.

External Port	Internal Port	Protocol	To IP address	Enabled
---	---	---	192 . 168 . 1 . 0	<input type="checkbox"/>
---	---	---	192 . 168 . 1 . 0	<input type="checkbox"/>
---	---	---	192 . 168 . 1 . 0	<input type="checkbox"/>
---	---	---	192 . 168 . 1 . 0	<input type="checkbox"/>
---	---	---	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
<input type="text"/>	<input type="text"/>	TCP	192 . 168 . 1 . 0	<input type="checkbox"/>

At the bottom of the page, there are 'Save Settings' and 'Cancel Changes' buttons. The Cisco Systems logo is visible in the bottom right corner.

- Now in one of the empty Application Fields fill in the below info.

Application Name	External Port	Internal Port	Protocol	To IP Address	Enabled
	---	---	---	192.168.1.0	<input type="checkbox"/>

**Application Name:** Viewtron

**External Port:** 9000

**Internal Port:** 9000

**Protocol:** TCP

**To IP address:** IP Address of the Viewtron DVR

**Check the Enable Box**

- Click the "**Save Settings**" button near the bottom of the screen.