

Linksys Router Port Forwarding Setup for iDVR-PRO 960H DVR

1. Log into your Linksys Router by typing the following gateway into a web browser <http://192.168.1.1> [By default Username and Password are both **admin**]
2. Once you are logged into your Linksys router click "**Applications & Gaming**" > "**Single Port Forwarding**". [If "Single Port Forwarding" is not an option than select "Port Range Forwarding"]

LINKSYS
A Division of Cisco Systems, Inc. Firmware Version: 1.01.35 build 3

Dual Band Wireless-N Gigabit Router with Storage Link VRT600N

Applications & Gaming

Setup Wireless Security Storage Access Restrictions **Applications & Gaming** Administration Status

Single Port Forwarding | Port Range Forwarding | Port Range Triggering | DMZ | QoS

Single Port Forwarding

Application Name

None

External Port	Internal Port	Protocol	To IP address	Enabled
...	192 . 168 . 1 . 0	<input type="checkbox"/>
...	192 . 168 . 1 . 0	<input type="checkbox"/>
...	192 . 168 . 1 . 0	<input type="checkbox"/>
...	192 . 168 . 1 . 0	<input type="checkbox"/>
...	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>
		TCP	192 . 168 . 1 . 0	<input type="checkbox"/>

Help...

Save Settings Cancel Changes

CISCO SYSTEMS

- Now in one of the empty Application Fields fill in the below info.

Application Name	External Port	Internal Port	Protocol	To IP Address	Enabled
	---	---	---	192.168.1.0	<input type="checkbox"/>

Application Name: iDVR-PRO 960H 1

External Port: 8080

Internal Port: 8080

Protocol: TCP

To IP address: IP Address of the DVR

Check the Enable Box

Repeat for ports 8080 and 5554

- Click the "**Save Settings**" button near the bottom of the screen.